
60W USB/BT/FM PLAYER MIXER AMPLIFIER WITH 6 ZONES



6 x 6 matrix amp/mixer with integrated media player, bluetooth connectivity, phantom power, FM radio + DAB and remote control included.

Reference: ZZONE6060PA

6-Zone 60W Mixer Amplifier

6 x 6 matrix amplifier/mixer with integrated multimedia player, Bluetooth connectivity, phantom power, FM + DAB radio

Technical Specifications

- Power: 6 x 60 W
- Speaker outputs: 6 output zones, 100V or 70V & 4 Ohm-8 Ohm-16 Ohm
- Inputs: 3 x Mic, 4 x Line
- Frequency response: 80-16KHz
- Protections: Short circuit, clip, overload, and protection against high temperature
- Power supply: AC230V; 50-60Hz
- Phantom feeding
- Remote control included
- Dimensions: 484 x 320 x 88 mm
- Weight: 14.5 Kg

Want more information about our mixer amplifier?

[Contact us now!](#)